

CONDUCTOR COLOR CODE

Grounded Conductor

- White
- Gray
- Three continuous white stripes

Ungrounded Conductor

- Any color other than white, gray, or green

Equipment Grounding Conductor

- Green with one or more yellow stripes
- Bare

POWER WIRING COLOR CODE

120/240 Volt

Black	Phase 1
Red	Phase 2
Blue	Phase 3
White or with 3 white stripes	Neutral
Green	Ground

277/480 Volt

Brown	Phase 1
Orange	Phase 2
Yellow	Phase 3
Gray or with 3 white stripes	Neutral
Green with yellow stripe	Ground

POWER-TRANSFORMER COLOR CODE

Wire Color

Transformer Circuit Type

Black	If a transformer does not have a tapped primary, both leads are black.
Black	If a transformer does have a tapped primary, the black is the common lead.
Black and Yellow	Tap for a tapped primary.
Black and Red	End for a tapped primary.